



601 FlagHouse Drive
Hasbrouck Heights, NJ 07604-3116
www.flaghouse.com

SPARKLING CARPET PANEL (US Item # 37902; CN Item # 379r02)

ABOUT THIS PRODUCT

The black carpet inside the panel has optical fibers woven into the pile, providing wonderful tactile and visual stimulation.

An A switch is included. Insert the jack socket at the bottom front of the panel.

CONTENTS

- (1) Sparkling Carpet Panel
- (1) 'A' Switch

PLEASE NOTE: Fixings are not included. See below.

TO ATTACH TO WALL

IMPORTANT: This panel weighs approximately 46 lbs. Please take this into consideration when fixing. Please make sure that you are aware of the wall's construction to which the panel is to be affixed. Taking this into account please ensure that you use the correct fittings. You may wish to attach two mirror plates to the back of the panel at the top and two on the back at the bottom.

Note: When attaching fixings to the back of the panel please proceed with caution. Be aware that there are electrical assemblies inside the panel.

MAINTENANCE

PLEASE NOTE: Before attempting any maintenance, switch off the power at the mains supply (i.e. unplug this panel.)

TO CHANGE LAMPS/FUSES

Unplug. Remove panel from wall and lay it on a flat surface e.g. floor. Remove the front cover.

LAMPS

1. The lamps are 12V, 20W, 1.4" Dichroic 10 degrees Spotlamps.
2. Remove the color drum by slackening the grub screw in the boss.
3. Pull the lamp from its socket carefully and replace with a new one. Do NOT touch the inside of the lamp.
4. Refit the color drum.
5. If the colors cease to change it is likely the drum motor or gear box has failed. Do NOT run the panel in this condition as permanent damage to the drum may result from the concentrated heat from the lamp. Please seek advice.

SPECIFICATION

MOTOR

12V synchronous (1.2 RRM 50Hz)

FUSES

The fuse is a T3.15Amp, front-mounted push in fuse holder located on the front of the electronics.

Output Fuse

T4 Amp fuse (in power supply—unscrew the fuse holders.)

Input Fuse

T3.15Amp fuse (in power supply. Unscrew the fuse holders.)

110V—T630mA: In the event of product failure, check the fuses in the following order: Input, Output, and Electronics.

POWER SUPPLY

Model SPS 60

Input: 230 Volts AC 50-60Hz (115 Volts AC 50-60 Hz)

Output: 12 Volts AC 60 Watts

SAFETY

Always supervise the use of this product.

For indoor use only.

Handle with care.

In the unlikely event of product failure, please seek advice. Only a qualified person should attempt repair.

DISCLAIMER: THIS PRODUCT MUST ALWAYS BE USED UNDER THE DIRECT SUPERVISION OF A CARE GIVER.

To ensure safety, this product must be assembled, installed and used in strict conformity with the instructions and specifications provided. All warranties of any kind, including, but not limited to, warranties of merchantability or fitness for a particular purpose, are expressly disclaimed and no warranty of any kind is implied or expressly made. FlagHouse shall not be liable for any direct, indirect, special, incidental, or consequential damages arising or resulting from the sale, use, replacement, or repair of this product.

Please direct your questions or concerns regarding this product to the appropriate office listed below:

In the U.S.

FlagHouse, 601 FlagHouse Drive, Hasbrouck Heights, NJ 07604-3116

Phone 800-793-7900

Fax 800-793-7922

Email info@flaghouse.com

In Canada

FlagHouse Canada, 235 Yorkland Blvd., Suite 105, North York, Ontario M2J 4Y8

Phone 800-265-6900

Fax 800-265-6922

Email flaghousecanada@flaghouse.com

International Customers

FlagHouse, 601 FlagHouse Drive, Hasbrouck Heights, NJ 07604-3116

Phone 201-288-7600

Fax 201-288-7887

8AM-6PM Eastern Time